

P-760

Channel				Function	DMX Value	Feacture
17CH	12CH	9CH	7CH			
1	1	1	1	Red	0~65535	
2				Red 16Bit		
3	2	2	2	Green	0~65535	
4				Green 16Bit		
5	3	3	3	Blue	0~65535	
6				Blue 16Bit		
7	4	4	4	White	0~65535	
8				Whiet 16Bit		
9	5			Colour Temperature	0~3	NO Used
					4,5	10000
					6,7	8000
					8,9	7000
					10,11	6500
					12,13	5600
					14,15	4200
					16,17	3200
					18,19	2700
					20~255	10000~2700

Favolite

Foshan Favolite Stage Lighting Co., Ltd

10	6			Colour Macro	0~1	No Function
					2,3	All Lights Up
					4,5	Red
					6,7	Yellow
					8,9	Green
					10,11	Cyan
					12,13	Blue
					14,15	Purple
					16~239	Colour Macro
					16~17	LEE 013
					18~19	LEE 021
					20~21	LEE 135
					22~23	LEE 122
					24~25	LEE 088
					26~27	LEE 131
					28~29	LEE 724
					30~31	LEE 161
					32~33	LEE 721
					34~35	LEE 104
					36~37	LEE 703
					38~39	LEE 795
					40~41	LEE 793
					42~43	LEE 332
					44~45	LEE 113
					46~47	LEE 108
					48~49	LEE 109
					50	LEE 242
					51	LEE 202
					52	LEE 709
					53	LEE 110
					54~74	LEE 328
					75~80	LEE 332
					81~82	LEE 113
					83~95	LEE 026
					96~101	LEE 022
					102~108	LEE 158
					109~114	LEE 768
					115~124	LEE 100
					125~134	LEE 088
					135~144	LEE 122
					145~150	LEE 089
					151	LEE 322
					152~155	LEE 124
					156~158	LEE 115
					159~163	LEE 353
					164~179	LEE 724

Favolite

Foshan Favolite Stage Lighting Co., Ltd

11	7	5	5	Strobe	0~7	No Function
					8~67	Pulse Shutting From Slow To Fast
					68~107	15% Shutting From Slow To Fast
					108~147	50% Flashing From Slow To Fast
					148~187	15% Flashing From Slow To Fast
					188~247	Pulse Flashing From Slow To Fast
					248~251	Sync Random Strobe
					252~255	Asynchronous Random Strobe
12	8	6	6	Dimmer	0~65535	
13				Dimmer 16Bit		
14	9	7		Dimmer Frequency & Curve Properties	0~31	806Hz-Exponential Curve
					32~63	806Hz-Linear
					64~95	1562Hz-Exponential Curve
					96~127	1562Hz-Linear
					128~159	5000Hz-Exponential Curve
					160~191	5000Hz-Linear
					192~223	8333Hz-Exponential Curve
					224~255	8333Hz-Linear
15	10			Dimmer Fade Speed	0~7	Fastest And No Fade
					8~247	Slow To Fast
					248~255	Auto Fade
16	11	8	7	Zoom	0~255	Zoom From Wide To Narrow
17	12	9		Reset	0~19	No Function
					20~29	Reset All
					30~189	No Function
					190~199	Unlock The Setting Lock
					200~255	No Function